


- Safety transformers according to the European standard CEI EN 61558-1 and CEI EN 61558-2-6
- Primary and Secondary two chamber windings
- Encapsulation in epoxy resin
- Marking on primary side
- Tin-plated phosphor bronze pins
- Pins size: Ø 0,9 mm typ , length 4mm min
- Only electrically used pins are mounted
- 5000V dielectric strength between primary and secondary windings
- 100% tested
- Custom-made versions on request



## 1.5 VA - $t_a70/B$ ( 1.6VA - $t_a50/B$ )

Code	Primary (50-60Hz)	Secondary <sup>1</sup> $t_a70^\circ$	Secondary <sup>1</sup> ( $t_a50^\circ$ )	Layout	Overload Protection
1011S106	230V	6V - 250 mA	(6V - 267 mA)	Drawing 1	inherently short-circuit proof
1011S109	230V	9V - 167 mA	(9V - 178 mA)	Drawing 1	inherently short-circuit proof
1011S112	230V	12V - 125 mA	(12V - 133 mA)	Drawing 1	inherently short-circuit proof
1011S115	230V	15V - 100 mA	(15V - 107 mA)	Drawing 1	inherently short-circuit proof
1011S118	230V	18V - 83 mA	(18V - 89 mA)	Drawing 1	inherently short-circuit proof
1011S124	230V	24V - 63 mA	(24V - 67 mA)	Drawing 1	inherently short-circuit proof
1011S206	230V	2x 6V - 125 mA	(2x 6V - 133 mA)	Drawing 2	inherently short-circuit proof
1011S209	230V	2x 9V - 83 mA	(2x 9V - 89 mA)	Drawing 2	inherently short-circuit proof
1011S212	230V	2x 12V - 63 mA	(2x 12V - 67 mA)	Drawing 2	inherently short-circuit proof
1011S215	230V	2x 15V - 50 mA	(2x 15V - 53 mA)	Drawing 2	inherently short-circuit proof
1011T106	115V	6V - 250 mA	(6V - 267 mA)	Drawing 1	inherently short-circuit proof
1011T109	115V	9V - 167 mA	(9V - 178 mA)	Drawing 1	inherently short-circuit proof
1011T112	115V	12V - 125 mA	(12V - 133 mA)	Drawing 1	inherently short-circuit proof
1011T115	115V	15V - 100 mA	(15V - 107 mA)	Drawing 1	inherently short-circuit proof
1011T118	115V	18V - 83 mA	(18V - 89 mA)	Drawing 1	inherently short-circuit proof
1011T124	115V	24V - 63 mA	(24V - 67 mA)	Drawing 1	inherently short-circuit proof
1011T206	115V	2x 6V - 125 mA	(2x 6V - 133 mA)	Drawing 2	inherently short-circuit proof
1011T209	115V	2x 9V - 83 mA	(2x 9V - 89 mA)	Drawing 2	inherently short-circuit proof
1011T212	115V	2x 12V - 63 mA	(2x 12V - 67 mA)	Drawing 2	inherently short-circuit proof
1011T215	115V	2x 15V - 50 mA	(2x 15V - 53 mA)	Drawing 2	inherently short-circuit proof

Dimensions	mm	Drawing 1 (bottom view)	Drawing 2 (bottom view)
a max	32,6		
b max	28,0		
h max	22,1		
x typ	5,0		
y typ	20,0		

<sup>1</sup> Rated voltage (No load voltage x 1,52).