

EI series 1620 - 15VA

- Safety transformers according to the European standard CEI EN 61558-1 and CEI EN 61558-2-6
- Primary and Secondary two chamber windings
- Encapsulation in epoxy resin
- Marking on primary side
- Tin-plated phosphor bronze pins
- Pins size: $\varnothing 0,9$ mm typ , length 4mm min
- Only electrically used pins are mounted
- 5000V dielectric strength between primary and secondary windings
- 100% tested
- Custom-made versions on request



15 VA - $t_a 70/B$



Code	Primary (50-60Hz)	Secondary ¹	Layout	Output fuses ²
1620S106	230V	6V - 2500 mA	Drawing 1	fuse 2500 mA
1620S109	230V	9V - 1667 mA	Drawing 1	fuse 1600 mA
1620S112	230V	12V - 1250 mA	Drawing 1	fuse 1250 mA
1620S115	230V	15V - 1000 mA	Drawing 1	fuse 1000 mA
1620S118	230V	18V - 833 mA	Drawing 1	fuse 800 mA
1620S124	230V	24V - 625 mA	Drawing 1	fuse 630 mA
1620S206	230V	2x 6V - 1250 mA	Drawing 2	2 fuses 1250 mA
1620S209	230V	2x 9V - 833 mA	Drawing 2	2 fuses 800 mA
1620S212	230V	2x 12V - 625 mA	Drawing 2	2 fuses 630 mA
1620S215	230V	2x 15V - 500 mA	Drawing 2	2 fuses 500 mA
1620S218	230V	2x 18V - 417 mA	Drawing 2	2 fuses 500 mA
1620T106	115V	6V - 2500 mA	Drawing 1	fuse 2500 mA
1620T109	115V	9V - 1667 mA	Drawing 1	fuse 1600 mA
1620T112	115V	12V - 1250 mA	Drawing 1	fuse 1250 mA
1620T115	115V	15V - 1000 mA	Drawing 1	fuse 1000 mA
1620T118	115V	18V - 833 mA	Drawing 1	fuse 800 mA
1620T124	115V	24V - 625 mA	Drawing 1	fuse 630 mA
1620T206	115V	2x 6V - 1250 mA	Drawing 2	2 fuses 1250 mA
1620T209	115V	2x 9V - 833 mA	Drawing 2	2 fuses 800 mA
1620T212	115V	2x 12V - 625 mA	Drawing 2	2 fuses 630 mA
1620T215	115V	2x 15V - 500 mA	Drawing 2	2 fuses 500 mA
1620T218	115V	2x 18V - 417 mA	Drawing 2	2 fuses 500 mA

Dimensions	mm	Drawing 1 (bottom view)	Drawing 2 (bottom view)
a max	51,4		
b max	43,3		
h max	41,3		
x typ	5,0		
y typ	27,5		

¹ Rated voltage (No load voltage x 1,19).

² See the output fuses notes on back cover. Different overload protection are possible if the user performs proper tests to assure the relevant standard compliance.